

QUICK START GUIDE


Infinea® X DF

For iPhone® 6s/7/8




Assemble Your Infinea X DF

1. Ensure the iOS device is set to Ring mode, and then open the unit by loosening the socket-head hex screws, and gently flip open the top cover.
2. Slide the iOS device onto the Lightning™ connector until it clicks into place.



3. Close the top cover while maintaining the position of the protective rubber bumper.

Note:
Before closing the top cover, wipe the interior glass with a clean, lint-free cloth to ensure your screen is clean and free from moisture.



4. Secure the cover by tightening the six flat-head T6 screws inserted into the upper enclosure.

Note:
Do not over tighten the screws as that may damage to cover.



Important:
The rubber bumper must be properly aligned between the top and bottom covers. If not, the liquid protection features of the Infinea X DF are compromised. If you have any questions about installation of the rubber bumper, contact your Infinite Peripherals account representative.



1. iPhone receiver port
2. Flat-head T6 screws (6)
3. iOS device On/Off button
4. Scan button
5. Status LEDs
6. Programmable button
7. Home button
8. Battery status button
9. Volume buttons



10. iOS device camera opening
11. Barcode scanner
12. RFID antenna
13. Battery pack
14. Battery latch

Battery LED Status Indicators

Press the battery status button (see number 8 above) to view the LEDs.

Status	Description
100% to 75%	Solid green
74% to 50%	Blinks green
49% to 25%	Blinks orange
24% to 10%	Blinks red
9% to 1%	One LED blinks red indicating emergency low battery



Charge the Infinea X DF

Two options are available for charging the Infinea X DF, via an AC wall outlet or by replacing the battery.

1. Attach the charging cup to the bottom of the unit.
2. Connect the USB end of the cable into the AC wall adapter (not included).

Note:

The AC adapter must support at least 2.1-amp. If you use less current than a device requires, it takes longer to charge. Refer to the Battery LED Status Indicators on page 1.

Sync with iTunes®

By design, your iPhone syncs with iTunes while connected to the Infinea X DF.

1. In the SDK, enable the Pass Through Sync option.
2. Connect the Infinea X DF to a computer using the charging cup.

Note:

To integrate the Infinea X with your iOS device's application, install our mobile device SDK. For the latest SDK, go to <https://developer.ipcmobile.com>.

Troubleshooting

iOS device does not sync with iTunes:

- Infinea X DF is not configured for sync.

Swiping card not detected by iOS device:

- Top cover is not properly installed.

iOS device does not charge:

- AC adapter may not meet charging requirements.
- Pass-Through-Sync is enabled.

Accessories & Additional Information

Contact your Infinite Peripherals sales representative for technical specifications and additional product documentation. For current and future offerings, visit our website, <https://ipcmobile.com/products/accessories>, or contact your Infinite Peripherals account representative for information about available chargers and battery packs for the Infinea X DF.

These charging accessories are available for the Infinea X DF:

- 10-Station Battery Charger
- 5-Unit Charging Station
- Charging Cup

Warnings & Cautions

Please observe the following precautions:

- Keep your unit dry since precipitation, humidity, and any liquid can corrode the electronic circuits.
- Do not store in dusty or dirty areas.
- Do not drop or kick the unit.
- Do not open the unit since only qualified staff at Infinite Peripherals can open the unit for repair.
- If your unit is not operating, go to <https://ipcmobile.com/support> for help.

Product Returns

Use the link in step 1 to create an account and gain access to our Knowledge Base and online support services. Through our online support center, you'll be able to download files, open a Support Ticket, manage your RMAs, view your account Profile and subscribe to Alerts.

To request a RMA

1. Create a user account in the RMA Support Portal at <https://ipcmobile.com/support/rma>
2. Login to your user account, and then click Create RMA Request.
3. Read the instructions provided and complete the online request form.
4. Note the assigned RMA number and write it clearly on your shipping carton.
5. Ship your equipment to us using the address provided.

Warranty

Infinite Peripherals does not warrant, and is not responsible for, any damage to the Infinea X DF ("Product") as a result of liquid or solid particle intrusion into the Product or damage caused by dropping the Product. If a material or workmanship defect arises with regard to any Infinite Peripherals product, and a valid claim is received within the Warranty Period, Infinite Peripherals (at Infinite Peripherals' sole discretion) will (1) repair the Product using new or refurbished parts, or (2) replace the Product with a new or refurbished Product. For purposes of this limited warranty, "refurbished" means a product or part that has been substantially returned to its original specifications. In the event of a defect, these are your exclusive remedies. Box contents and part numbers may vary based on your order configuration.

SKUs: IX-Z2DBTR-PH7-LG; IX-Z2DBTR-PH7-MG; IX-Z2DBTR-PH8-LG; IX-Z2DBTR-PH8-MG

Contact Information

Mobility Sales/ Technical Support Center

Infinite Peripherals, Inc.
17681 Mitchell N
Irvine, CA 92614
Toll-Free: (866) 278-7860
Office: (949) 222-0300
Email: info@ipcmobile.com
Website: ipcmobile.com

Headquarters/ Main Warehouse

Infinite Peripherals, Inc.
2312 Touhy Avenue
Elk Grove Village, IL 60007
Toll-Free: (800) 278-7860
Office: (847) 818-1260
Fax: (847) 818-1287