

QUICK START GUIDE


Pistol Grip

For Linea Pro® 5




Assemble Pistol Grip


1. Insert the Linea Pro 5 into the silicone sleeve for assembly.




2. Angle the assembly into the pistol grip, and then onto the mini USB to connect the pistol grip USB ribbon.



3. Insert the assembly into the pistol grip, and then press into place snugly.



4. Insert the remaining assembly, and press it securely in place.
5. Tuck the silicone sleeve into the pistol grip casing neatly.



Scan Barcodes

1. Press the pistol grip trigger to activate the scanner.
 2. Position the scan head near the center of a barcode.
- Note:
The pointer should extend outside of the edges of the barcode.
3. Pull the pistol grip back slowly increasing the distance between the barcode and scan head until the barcode is read by the scanner.

Charge Pass-Through

The pistol grip is designed to

- Charge from the bottom of the handle.
- Support pass-through charging to the iOS device using a USB to AC adapter or a station charger accessory.

Note:

During pass-through charging, the pistol grip only begins to charge after the iOS device is fully charged.

USB Port

Insert the mini USB cable (provided with your LP5) into the USB port on the bottom of the pistol grip.

Charging Station Accessory

Before charging your pistol grip with a charging station accessory, refer to the product documentation provided by the manufacturer for proper instructions.

Caution:

To prevent electrical damage to your pistol grip and/or battery, ensure only an approved 5V/2.1 AC adapter is used.

Battery Level Status

Press the battery status button to view the **solid** LED lights.

Status	Description
0-25%	One LED
26%-50%	Two LEDs
51%-75%	Three LEDs
74%-100%	Four LEDs

Charge Status

Charge status is indicated by **flashing** LEDs.

Status	Description
0-25%	1st LED flashes
26%-50%	2nd LED flashes
51%-75%	3rd LED flashes
76%-99%	4th LED flashes
100%	All four LEDs flash





Features

These items are required to use the Linea Pro 5 Pistol Grip (Model# CS-LP5-PG):

- Linea Pro 5 unit
- iOS devices: iPod® Touch 5th generation or iPhone® 5/5s
- mini USB charging cable
- Charging contacts or mini USB cable
- Charging switch to turn on the pistol grip and enable back-up charge mode
- Mini LED battery indicators for charge status and battery levels.

Troubleshooting

Barcode scanner does not turn on.

- Pistol Grip is not connected to the Linea Pro 5
- Linea Pro 5 is not connected to the iOS device

The following SDK settings are not properly configured:

- Scan Button – Enabled
- Pass Through Sync – Disabled (if Back-up charge is enabled)

LEDs do not indicate battery level

- Charging switch is not set to Back Up Charge mode
- Pistol Grip is not plugged in through the USB cable

Pistol Grip is not charging iOS device or Linea Pro 5

- Charging switch is not set to Back-up charge mode
- Pistol Grip battery is fully discharged
- USB ribbon is not connected to Linea Pro 5

Accessories & Additional Information

For current or future offerings and additional product documentation, visit our website at <https://ipcmobile.com/devices/linea-pro-5> or contact your Infinite Peripherals account representative for complete details.

Note:

The iOS device and any other additional items shown may not be included in your order.

Product Returns

Use the link in step 1 to create an account and gain access to our Knowledge Base and online support services. Through our online support center, you'll be able to download files, open a Support Ticket, manage your RMAs, view your account Profile and subscribe to Alerts.

To request a RMA

1. Create a user account in the RMA Support Portal at <http://ipcmobile.com/support/rma/>
2. Login to your user account and then click Create RMA Request.
3. Read the instructions provided and complete the online request form.
4. Note the assigned RMA number and write it clearly on your shipping carton.
5. Ship your equipment to us using the address provided.

Warnings & Cautions

Please observe the following precautions:

- Keep the unit away from liquids. Do not immerse it in water.
- The unit is intended for indoor use only. When not in use, place it in a cool, dry place.
- Do not place the unit near a heat source. Keep both the power supply and unit away from direct sunlight and/ or heat.
- Unit should only be repaired by Infinite Peripherals.

Warranty

Infinite Peripherals does not warrant, and is not responsible for, any damage to the Linea Pro 5 Pistol Grip ("Product") as a result of liquid or solid particle intrusion into the Product or damage caused by dropping the Product. If a material or workmanship defect arises with regard to any Infinite Peripherals product, and a valid claim is received within the Warranty Period, Infinite Peripherals (at Infinite Peripherals' sole discretion) will (1) repair the Product using new or refurbished parts, or (2) replace the Product with a new or refurbished Product. For purposes of this limited warranty, "refurbished" means a product or part that has been substantially returned to its original specifications. In the event of a defect, these are your exclusive remedies.

Note:

Box contents and part numbers may vary based on your order configuration.

Contact Information

Mobility Sales/ Technical Support Center

Infinite Peripherals, Inc.

17681 Mitchell N

Irvine, CA 92614

Toll-Free: (866) 278-7860

Office: (949) 222-0300

Email: info@ipcmobile.com

Website: ipcmobile.com

Headquarters/ Main Warehouse

Infinite Peripherals, Inc.

2312 Touhy Avenue

Elk Grove Village, IL 60007

Toll-Free: (800) 278-7860

Office: (847) 818-1260

Fax: (847) 818-1287